



DB2016

2000 Series Isolator Base

General

The DB2016 isolator base senses and isolates overload and short circuit faults on a 2000 series fire detector loop. A yellow LED on the device indicates an isolation condition. The detector connected to the DB2016 still receives power in the event of a single short circuit. If every detector in the loop is fitted with an isolator base, no devices are lost in the event of a single short circuit.

Functionality and use

The function of the DB2016 is to protect the integrity of the addressable loop in the case of an overload or short-circuit on part of the loop. In such event, the entire data circuit is not lost but only the effected part of the loop is isolated.

For full protection it is recommended that every detector be fitted with a DB2016 isolator base. For regulatory purposes it is specified that not more than a single detection zone is affected by a single fault on the loop, containing no more than 32 devices.

The DB2016 is only suitable for use in dry areas.



Details

- Protection against overload conditions
- Automatic restore when fault is corrected
- LED indicates isolation condition
- Detector connected to isolator remains operational

DB2016

2000 Series Isolator Base

Technical specifications

Electrical

Operating voltage	17 to 34 V (28 V nominal)
Current consumption	30 μ A (standby) < 1.6 mA (isolated) 800 mA (passing current (max))

Physical

Physical dimensions	100 x 13 mm (\varnothing x H)
Net weight	47 g
Colour	Cloud white (RAL 9001)

Environmental

Operating temperature	-10 to +50°C
Relative humidity	0 to 95% noncondensing
Environment	Indoor
IP rating	IP30

Standards & regulation

Certification	EN54-17
---------------	---------

Line resistance

Normal	0.1 Ohms
--------	----------

Switching voltage

Normal to isolated	14 V
Isolated to normal	14.5 V

Isolation line

Negative breaking isolator

