

# PRS-CSNKP Numeric Keypad

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Numeric keypad for zone selection and user access
- ▶ Serial data and power interface to call-station basic
- ▶ Can be combined with normal call-station keypads
- ▶ LCD for user feedback
- ▶ Stylish and modern design

The Call-Station Numeric Keypad is used in combination with a basic or remote call-station. The call-station provides the microphone and press-to-talk key, while the numeric keypad can be used for user access, zone and zone group selection. It works together with call-station keypads for pre-configured actions. The built-in LCD provides feedback to the user.

## Functions

The call-station numeric keypad has a 12-key numeric keypad, providing a telephone-like user interface with \*, # and 0...9 keys. A single numeric keypad connects directly to a basic or remote call-station and subsequently up to 15 other keypads can be linked for controlling functions. It is mechanically fixed to the call-station. The numeric keypad can be configured for the following functions:

- User access to the call-station with user number and PIN, configurable for multiple users, with time-out and manual lock
- Selecting zones and zone groups as destinations for calls; up to eight zones and/or zone groups can be entered into a string.

The LCD gives feedback to the user about the selections and the status of the selected zones and zone groups.

The keypad gets its power supply from the connected call-station. It is configured via the Preasideo network controller (web browser interface).

## Controls and indicators

- 12 numeric keys
- 2 x 16 character LCD with backlight
- LCD brightness adjustment
- LCD contrast adjustment

## Interconnections

- Flat-cable connection to call-station
- Flat-cable connection to next keypad

## Certifications and approvals

|           |  |
|-----------|--|
| Safety    | acc. to IEC 60065 / EN 60065                 |
| Immunity  | acc. to EN 55103-2 / EN 50130-4 / EN 50121-4 |
| Emissions | acc. to EN 55103-1 / FCC-47 part 15B         |
| Emergency | acc. to EN 60849 / EN 54-16 / ISO 7240-16    |
| Maritime  | acc. to IEC 60945                            |

| Region | Certification |           |
|--------|---------------|-----------|
| Europe | CPR           | EU_CPR    |
|        | CE            |           |
|        | CE            | COC       |
|        | CE            | CertAlarm |
|        | CE            | DOP       |
|        | GL            |           |

### Parts included

| Quantity | Component                |
|----------|--------------------------|
| 1        | PRS-CSNKP Numeric Keypad |
| 1        | Flat-cable               |
| 1        | Coupling bracket         |

### Technical specifications

#### Electrical

|                   |            |
|-------------------|------------|
| Power consumption | 1.8 W (DC) |
|-------------------|------------|

#### Mechanical

|                        |  |
|------------------------|--|
| Dimensions (H x W x D) | 70 x 95 x 200 mm (2.8 x 3.7 x 7.9 in)                |
| Weight                 | 0.4 kg (0.9 lb)                                      |
| Mounting               | Bracket attachment to a call-station or other keypad |
| Color                  | Charcoal   |

#### Environmental

|                       |                                     |
|-----------------------|-------------------------------------|
| Operating temperature | -5 °C to +45 °C (+23 °F to +113 °F) |
| Storage temperature   | -20 °C to +70 °C (-4 °F to +158 °F) |
| Relative humidity     | 15% to 90%                          |
| Air pressure          | 600 to 1100 hPa                     |

### Ordering information

#### PRS-CSNKP Numeric Keypad

Call station numeric keypad and LCD for controlled user access and zone selection in large systems, can be combined with call station keypads.

Order number **PRS-CSNKP**

#### Represented by:

##### Americas:

Bosch Security Systems, Inc.  
12000 Portland Avenue South  
Burnsville MN 55337, USA  
Phone: +1-800-392-3497  
Fax: +1-800-955-6831  
audiosupport@us.bosch.com  
www.boschsecurity.com

##### Europe, Middle East, Africa:

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

##### Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

##### China:

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

##### America Latina:

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com